



THANK YOU FOR YOUR PURCHASE OF THIS PRODUCT OF P!PES

FEATURES:

- LIGHTWEIGHT MAIN CIRCUITBOARD
- 12 LEDS IN VARIOUS COLORS
- UNIQUE BICOLOR LEDS (RED & BLUE)
- 12 DIFFERENT LIGHT SEQUENCES
- IF PREFERRED, SWITCHABLE WITH THE THIRD CHANNEL FROM YOUR RECEIVER, NO SWITCH REQUIRED
- ULTRACOOL BI-COLOR LED SEQUENCES

USER MANUAL:

THIS LIGHT UNIT MUST BE CONNECTED DIRECTLY TO YOUR 3RD CHANNEL. YOU CAN SWITCH THROUGH THE 12 DIFFERENT SEQUENCES USING THE 3RD CHANNEL SWITCH ON YOUR REMOTE.

ONCE INSTALLED, SIMPLY TURN ON THE POWER OF YOUR MACHINE, AND THE LIGHTS WILL BEGIN TO WORK.

EACH TIME YOU PRESS THE 3RD CHANNEL BUTTON ON YOUR REMOTE, IT WILL CHANGE TOWARDS THE NEXT SEQUENCE UNTIL YOU HAVE FOUND THE RIGHT SEQUENCE.

WHEN YOU TURN THE POWER OFF, THE LIGHTUNIT WILL AUTOMATICALLY STARTS AGAIN AT SEQUENCE 0 (LIGHTS OFF) ONCE THE CAR IS TURNED BACK ON.

SPECS:

- LEDS: 8X WHITE LED 5MM AND 4X BI-COLOR LED 3MM (RED & BLEU)
- WEIGHT: 20 GRAM.
- LENGHT LED CABLE: 30CM.
- LENGHT SERVO CABLE: 15CM.
- DIMENSIONS OF CIRCUITBOARD: 30MM X 18MM.
- OPERATING VOLTAGE: 4.8V - 6.0V.

GUARANTEE:

ALL SYSTEM COMPONENTS ARE GUARANTEED AGAINST MANUFACTURER DEFECT FOR 2 YEARS AFTER THE ORIGINAL DATE OF PURCHASE.

- WARRANTY DOES NOT COVER DAMAGE DUE TO POWERING THE LED BEYOND SPECIFIED RATINGS.
- WARRANTY DOES NOT COVER DAMAGE DUE TO AN INCORRECT INSTALLATION.
- WARRANTY DOES NOT COVER ABNORMAL WEAR, ABUSE, NEGLECT, OR ANY DAMAGE ARISING AS A RESULT OF IMPROPER USE OR MODIFICATION. AVOID WATER WHILE USING IN CASE OF SHORT-CIRCUIT. AND DON'T LOOK IN THE LED, OFFCOURSE.

HAVE FUN WITH YOUR PRODUCT!!!